



# GFE-BCM-3

## PSU WITH BATTERY CHARGER MODULE

This unit is a fully EN54-4 compliant PSU incorporating a battery charger that can be used with all of GFE's addressable and conventional panels. It will monitor all fault conditions including: charger fault, charger voltage level, input voltage supply fault and supply removal. It is supplied boxed in an ABS plastic enclosure, including a 28V DC @ 1.7 or 2.4 Amp PSU.

### KEY FEATURES

- Battery charger monitored
- Fault relay output
- Low battery voltage shutdown
- Reverse polarity protection
- Battery charger current regulated
- LED indicators: AC ON, Battery & Charger Fault
- Boxed unit inc. PSU and battery compartment
- Fully compliant with EN54-4

### TECHNICAL SPECIFICATIONS

SUPPLY INPUT	230 +10% -15% V AC - Monitored
SUPPLY OUTPUT	1.7A or 2.4 A @ 28V DC nominal
BATTERY CHARGER - CURRENT O/P	1A max.
BATTERY TYPE	Max. 2 x 12V 7AH - Lead Acid VRLA
BATTERY FUSE	3A
FAULT RELAY	Changeover - 30V DC 1A Resistive
OPERATION TEMPERATURE	-10°C to +50°C
MAX. HUMIDITY / PROTECTION	95% RH Non-Condensing / IP21
DIMENSIONS	273 (L) x 404 (H) x 107 (W) mm
WEIGHT	1.7 Kg - 7 Kg inc 2 x 7AH Bat.

### ORDER CODE

<b>GFE-BCM-3 (1.7A)</b>	BATTERY CHARGER MODULE - 28V DC 1.7A PSU - BOXED
<b>GFE-BCM-3 (2.4A)</b>	BATTERY CHARGER MODULE - 28V DC 2.4A PSU - BOXED